



FUSION INSTALL



Installation
Included



SureIQ
Technology



Voice, Text
& Data



All
Carriers



Double the
Power

SureCall Fusion Install

Cell Phone Signal Booster Plus Home Installation

Overview

Boost cell signal inside any home with SureCall's Fusion Install, the most powerful cellular signal booster kit that provides strong, reliable connections inside any residence from 2 rooms to whole house coverage. The Fusion Install bundle includes professional installation for residences and homes only through our trusted install partner OnTech Smart Services.

Assembled and tested in the USA with outstanding build quality, award-winning technologies, all-carrier compatibility, and world-class support, the Fusion Install is the premier cell phone signal booster in any large residence.

- Significantly improve cellular connectivity for all US cell carriers and devices inside any home
- 2XP technology delivers twice the uplink power to the tower when compared to the closest competitor to stay connected with distant cell towers
- Patented SureIQ technology balances incoming signals, ensuring continuous uptime and peak performance in urban, suburban and rural areas
- Highest system gain in its class combined with our strongest outdoor yagi antenna ensures constant connectivity in even the most challenging signal environments
- 5G Compatible - Fusion Install supports 4G and 5G devices
- Assembled and tested in the USA. FCC and IC-approved amplifiers built with the highest quality materials for longevity and connectivity when you need it most
- Includes 24/7 lifetime US-based tech support and 3-year manufacturer's warranty

Note: Installation included for residential homes in the USA only. For offices and commercial business installs please contact us directly at sales@surecall.com

Package Contents

Kit includes: Fusion Install amplifier, 50 ft of low loss RG-11 coax cable, 20 ft of low loss SC-240 coax cable, outdoor Yagi antenna and indoor panel antenna.

Outside Components



Yagi, Directional



RG-11, 50 ft,
optional adaptor



Booster and
Power Supply



SC-240, 20 ft



Panel,
Directional

Inside Components



Shown: Fusion Install signal booster kit

Specifications

| | |
|----------------------------------|---|
| Uplink Frequency Ranges (MHz): | 698-716 / 776-787 / 824-849 / 1710-1755 / 1850-1915 |
| Downlink Frequency Ranges (MHz): | 728-746 / 746-757 / 869-894 / 1930-1995 / 2110-2155 |
| Max Gain: | 72 dB |
| Impedance: | 75Ω in / 50Ω out |
| Max Uplink Power: | 26.0 dBm |
| Cable: | RG-11 (50 ft.) / SC-240 (20 ft.) |
| RF Connectors: | F Female (Outside) / N Female (Inside) |
| FCC ID | RSNF4HOME3 |

► Patent No. US 8,867,572 B1; US 9,100,839 B2



Pulse Supply
909 Ridgebrook Road., Sparks, Maryland 21152, USA
TEL : +1-410-583-1701 FAX : +1-410-583-1704
E-mail: sales@pulsesupply.com
<https://www.pulsesupply.com/surecall>



SureCall Fusion Install

Improving Indoor Cell Service Inside Any Residence


Specification

| Model No. | Fusion Install |
|---------------------------------|---|
| Uplink Frequency Range (MHz): | 698–716 / 776–787 / 824–849 / 1850–1915 / 1710–1755 |
| Downlink Frequency Range (MHz): | 728–746 / 746–757 / 869–894 / 1930–1995 / 2110–2155 |
| Supported Standards: | CDMA, WCDMA, GSM, EDGE, HSPA+, EVDO, LTE and all cellular standards |
| Impedance: | 75Ω donor port / 50Ω server port |
| Maximum Gain: | 72 dB |
| Noise Figure: | 8 dB |
| VSWR: | ≤2.0 |
| Max Uplink Power: | 26.0 dBm |
| Maximum Output Power: | 1 Watt EIRP |
| Cable: | RG-11 / SC-240 |
| RF Connectors: | F Female donor port / N Female server port |
| AC Power Transmitter: | Input AC 110V, 60 Hz; Output DC 5-15V |
| Power Consumption: | <15W |
| Dimensions: | 7.875 x 5 x 1.188 inches |
| Weight: | 2 lb 3 oz. |
| Certifications: | FCC: RSNF4HOME3 |

Specifications are subject to change. Specifications contained within apply only to products meeting the latest FCC Certification Guidelines.

Installation Example:

SureCall Fusion Install kit



Visit SureCall.com/OnTech to schedule your installation

Installation included for residential homes in the USA only. For offices and commercial business installs please contact us directly at sales@surecall.com